



This PDF is generated from authoritative online content, and is provided for convenience only. This PDF cannot be used for legal purposes. For authoritative understanding of what is and is not supported, always use the online content. To copy code samples, always use the online content.

Web Services API Reference

[List Devices](#)

12/17/2025

List Devices

This operation allows you to list devices.

Contents

- [1 List Devices](#)
 - [1.1 Requests](#)
 - [1.2 List Device URIs or Devices](#)
 - [1.3 List Device Fields](#)

Requests

Devices can be listed in the following groupings:

- **All devices in a contact center**
 - requires contact center admin role.
 - Path to be used: **.../api/v2/devices**
- **All devices assigned to a given user**
 - Requires contact center admin role.
 - Path to be used: **...api/v2/users/{userid}/devices**
- **All devices assigned to the current user**
 - Requires contact center agent or login role.
 - Path to be used: **...api/v2/me/devices**

List Device URIs or Devices

Request

The request can return the list of device URIs or the list of devices. To list uris:

```
GET .../devices
```

Response

```
{
  "statusCode":0,
  "uris":[
    "http://172.21.16.123:8080/cloud-web/api/v2/devices/0c754c1f-7a65-4a7f-9a2b-c5bb5c983653",
    "http://172.21.16.123:8080/cloud-web/api/v2/devices/406ff680-63c8-4eeb-8c23-f39f538059d1",
    "http://172.21.16.123:8080/cloud-web/api/v2/devices/d6186ffc-af3d-4925-835e-a9e8dad98051"
  ]
}
```

List Device Fields

Request

To list devices use the `fields=*` query parameter:

```
GET .../devices?fields=*
```

Response

```
{
  "statusCode":0,
  "devices":[
    {
      "id":"0c754c1f-7a65-4a7f-9a2b-c5bb5c983653",
      "deviceState":"Inactive",
      "phoneNumberUri":"http://172.21.16.123:8080/cloud-web/api/v2/phone-numbers/6658d431-9195-4184-a462-b8a6fd901de8",
      "telephonyNetwork":"Public",
      "model":"CloudDevice",
      "vendor":"Genesys",
      "phoneNumber":"+16509870000",
      "country":{"
        "name":"United States",
        "code":"US",
        "callingCode":"1"
      },
      "location":"California",
      "e164Number":"+16509870000",
      "voiceServiceUri":"http://172.21.16.123:8080/cloud-web/api/v2/services/b40eb01e-199d-4db3-a91f-a0cf104ab2bf"
    },
    {
      "id":"1fd21300-303d-401f-9b4c-0d9c2801433e",
      "deviceState":"Inactive",
      "phoneNumberUri":"http://172.21.16.123:8080/cloud-web/api/v2/phone-numbers/812a7b7b-0e5b-4025-9443-79363b85773c",
      "telephonyNetwork":"Public",
      "model":"CloudDevice",
      "vendor":"Genesys",
      "phoneNumber":"3001",
      "country":{"
        "name":"",
        "code":"",
        "callingCode":""
      },
      "e164Number":"3001",
      "voiceServiceUri":"http://172.21.16.123:8080/cloud-web/api/v2/services/b40eb01e-199d-4db3-a91f-a0cf104ab2bf"
    },
    ...
  ]
}
```