



This PDF is generated from authoritative online content, and is provided for convenience only. This PDF cannot be used for legal purposes. For authoritative understanding of what is and is not supported, always use the online content. To copy code samples, always use the online content.

Genesys Engage Digital (eServices)

license

12/16/2025

license

- `ics_custom_media_channel`
- `ics_email_webform_channel`
- `ics_live_web_channel`
- `ics_multi_media_agent_seat`
- `ics_sms_channel`
- `license-file`

ics_custom_media_channel

Default Value: 0

Valid Values: Any positive integer up to the number of licenses for the feature in the license file

Changes Take Effect: Immediately

Specifies the number of licenses to check out for this option license to support OpenMedia capabilities. Each login at a place uses one license per media type, not including e-mail, chat and sms. E-mail, chat and sms are not considered custom media and have their own options, `ics_email_webform_channel`, `ics_live_web_channel` and `ics_sms_channel` respectively.

ics_email_webform_channel

Default Value: 0

Valid Values: Any positive integer up to the number of licenses for the feature in the license file

Changes Take Effect: Immediately

Specifies the number of licenses to check out for this option license to support e-mail capabilities. Each login for media at a place uses one license. See "Media and Licensing Example" for an example of how to determine the number of licenses you need when supporting multiple media types.

ics_live_web_channel

Default Value: 0

Valid Values: Any positive integer up to the number of licenses for the feature in the license file

Changes Take Effect: Immediately

Specifies the number of licenses to check out for this option license to support chat capabilities. Each login for media at a place uses one license. See "Media and Licensing Example" for an example of how to determine the number of licenses you need when supporting multiple media types.

ics_multi_media_agent_seat

Default Value: 0

Valid Values: Any positive integer up to the number of licenses for the feature in the license file

Changes Take Effect: Immediately

Specifies the number of licenses to check out for this option license. This limits the total number of places that can be logged in, even without a media type. Each login at a place uses one license. See "Media and Licensing Example" for an example of how to determine the number of licenses you need when supporting multiple media types.

ics_sms_channel

Default Value: 0

Valid Values: Any positive integer up to the number of licenses for the feature in the license file

Changes Take Effect: Immediately

Specifies the number of licenses to check out for this option license to support SMS capabilities. Each login for media at a place uses one license. See "Media and Licensing Example" for an example of how to determine the number of licenses you need when supporting multiple media types.

license-file

Default Value:

Valid Values: Any valid port address in the format,

<your_license_server_port>@<your_license_server_host> or the full path to the license file

Changes Take Effect: At start/restart

Specifies the location of the license file.