



This PDF is generated from authoritative online content, and is provided for convenience only. This PDF cannot be used for legal purposes. For authoritative understanding of what is and is not supported, always use the online content. To copy code samples, always use the online content.

Genesys Voice Platform

ccpccxml Section

ccpccxml Section

- `default_uri`
- `defaultmaxage`
- `defaultmaxstale`
- `fips_enabled`
- `shutdown_grace_period`
- `sip.send_progressing`

default_uri

Default Value: file://\$InstallationRoot\$/config/default.ccxml

Valid Values:

Changes Take Effect: immediately

Specifies the URI for the default CCXML application

defaultmaxage

Default Value: 60

Valid Values: From 30 to 180 inclusive (in seconds)

Changes Take Effect: immediately

Default Maxage for fetching an initial CCXML page

defaultmaxstale

Default Value: 0

Valid Values: From 0 to 180 inclusive (in seconds)

Changes Take Effect: immediately

Default Maxstale for fetching an initial CCXML page

fips_enabled

Default Value: false

Valid Values: true, false

Changes Take Effect: At start/restart

Specifies whether to enable FIPS mode in CCP. When FIPS mode is enabled, only FIPS 140-2 approved ciphers and algorithms can be used in SSL connections.

shutdown_grace_period

Default Value: 7200

Valid Values: From 0 to 65535 inclusive (in seconds)

Changes Take Effect: immediately

The amount of time (in seconds) sessions are given to terminate after Graceful Stop is selected. Once this grace period is exceeded, sessions are killed by ccxml.kill.unconditional events.

sip.send_progressing

Default Value: 0

Valid Values: 1, 0

Changes Take Effect: immediately

Determines whether 180 SIP response is sent on <accept> tag for all incoming calls.

0 - 180 response is sent when <send> is called

1 - 180 response is sent immediately after sending 100 Trying