



This PDF is generated from authoritative online content, and is provided for convenience only. This PDF cannot be used for legal purposes. For authoritative understanding of what is and is not supported, always use the online content. To copy code samples, always use the online content.

Genesys Voice Platform

mediacontroller Section

12/14/2025

mediacontroller Section

- `allow_dialog_transfer`
- `bridge_server`
- `bridge_server.defaultmaxsize`
- `bridge_server.defaultreserve`
- `bridge_server.profile`
- `bridge_sips_server`
- `codec_check_exclusion.payloads`
- `conference.defaultreserve`
- `defaultrejectcode`
- `full_audio_codec`
- `full_video_codec`
- `inbound_allowed_media`
- `sdp.defaultipversion`
- `sdp.localhost`
- `sdp.localhost.ipv6`
- `sip.allowedunknownheaders`
- `sipproxy`
- `sipsecure`
- `sipsproxy`

allow_dialog_transfer

Default Value: 1

Valid Values:

- **true** Enable transfers through dialog
- **false** Disable transfers through dialog

Changes Take Effect: immediately

Allows SIP dialog transfer. If this parameter is set to false, all incoming SIP REFER will be automatically rejected with SIP 403. Otherwise, the request will be forward to the CCXML application.

bridge_server

Default Value: \$LocalIP\$:5060

Valid Values: A valid IP address:Port can only contain alphanumeric characters, '.', '-', ':', '/', and '\' characters

Changes Take Effect: immediately

The address of SIP Bridge Server for use when the two end-points cannot be joined due to media bridging limitations.

Bridge Server must be able to

- send media to multiple end-points
- send and receive from distinct end-points and
- have transcoding capability.

bridge_server.defaultmaxsize

Default Value: 4
Valid Values: From 1 to 1000 inclusive
Changes Take Effect: immediately

This controls the confmaxsize URI parameter when conference is set up in the bridge server.

bridge_server.defaultreserve

Default Value: 4
Valid Values: From 1 to 1000 inclusive
Changes Take Effect: immediately

This controls the confreserve URI parameter when conference is set up in the bridge server.

bridge_server.profile

Default Value: Default Conference
Valid Values:
Changes Take Effect: immediately

The name of device profile to use with the configured Bridge Server.

bridge_sips_server

Default Value: \$LocalIP\$:5061
Valid Values: A valid IP address:Port can only contain alphanumeric characters, ':', '-', ';', '/', and '\' characters
Changes Take Effect: immediately

The address of SIP secure Bridge Server for use when the two end-points cannot be joined due to media bridging limitations.

Bridge Server must be able to

- send media to multiple end-points
- send and receive from distinct end-points and
- have transcoding capability.

codec_check_exclusion.payloads

Default Value: 13
Valid Values:
Changes Take Effect: immediately

A list of space delimited payloads that will be excluded during codec checking for join result determination.

conference.defaultreserve

Default Value: 8

Valid Values:

Changes Take Effect: immediately

Default URI confreserve parameter for conference server if requested reserve size is not defined

defaultrejectcode

Default Value: 480

Valid Values:

Changes Take Effect: immediately

Specifies the default SIP Response code to use when an incoming call is rejected by the application

full_audio_codec

Default Value: 0|pcmu|audio/basic|8000|1 8|pcma|audio/x-alaw-basic|8000|1 9|g722|audio/g722|8000|1 23|g726-16|audio/g726-16|8000|1 22|g726-16|audio/g726-16|8000|1 2|g726-32|audio/g726|8000|1 125|g726-40|audio/g726-40|8000|1 18|g729|audio/g729|8000|1 3|gsm|audio/x-gsm|8000|1 105|AMR|audio/AMR|8000|1 112|AMR-WB|audio/AMR-WB|16000|1 101|telephone-event|none|8000|1

Valid Values:

Changes Take Effect: immediately

This defines the audio codecs that get set in the SDP in an initial offer with no media bridge. Codec entry has to be in the format of: payload|name|mime|rate|#channels. Each codec entry is separated by a whitespace.

full_video_codec

Default Value: 34|h263|video/H263|90000|1 99|h263-1998|video/H263-1998|90000|1 113|H264|video/H264|90000|1

Valid Values:

Changes Take Effect: immediately

This defines the video codecs that get set in the SDP in an initial offer with no media bridge. Codec entry has to be in the format of: payload|name|mime|rate|#channels. Each codec entry is separated by a whitespace.

inbound_allowed_media

Default Value: dynamic

Valid Values: Must be one of the following:

- **dynamic**
- **audio video**
- **audio**
- **video**

Changes Take Effect: immediately

The default allowed media types for an inbound call. All inbound calls will be limited to this set of media types in terms of SDP exchange. If set to dynamic, media type is determined from the capability SDP of the inbound call (if capability SDP is not available, it defaults to audio and video).

sdp.defaultipversion

Default Value: true
Valid Values: ipv4, ipv6
Changes Take Effect: immediately

Default IP version to be used in SDP message, apply to initiated SDP offer to unjoined endpoint. Valid values are "ipv4" or "ipv6".

sdp.localhost

Default Value: \$LocalIP\$
Valid Values:
Changes Take Effect: immediately

The local host IPv4 address (only the host part) that will be used in SDP.

sdp.localhost.ipv6

Default Value: \$LocalIPv6\$
Valid Values:
Changes Take Effect: immediately

The local host IPv6 address (only the host part) that will be used in SDP.

sip.allowedunknownheaders

Default Value:

•

Valid Values:
Changes Take Effect: immediately

This parameter takes a space delimited list of acceptable unknown header list. Unknown headers received from SIP messages that are not part of this list will be ignored. It will not be accessible from the application. Specifying a wildcard (*) means all unknown headers are allowed.

sipproxy

Default Value: \$LocalIP\$:5060
Valid Values: A valid IP address:Port can only contain alphanumeric characters, '.', '-', ':', '/', and '\' characters
Changes Take Effect: immediately

The address of SIP Proxy for outbound SIP requests. Should be specified like 10.10.30.205:5070

sipsecure

Default Value: 0

Valid Values:

- **true** Using SIP Secure protocol

- **false** Not using SIP Secure protocol

Changes Take Effect: immediately

If this flag is set to true, all the outbound sip requests would be in SIP secure protocol. Note, the hints attribute of the CCXML elements that initiates an out bound request can over write this configuration.

sipsproxy

Default Value: \$LocalIP\$:5061

Valid Values: A valid IP address:Port can only contain alphanumeric characters, '.', '-', ':', '/', and '\' characters

Changes Take Effect: immediately

The address of SIP Secure Proxy for outbound SIP requests. Should be specified like 10.10.30.205:5071