



This PDF is generated from authoritative online content, and is provided for convenience only. This PDF cannot be used for legal purposes. For authoritative understanding of what is and is not supported, always use the online content. To copy code samples, always use the online content.

SIP Feature Server User's Guide

Accessing voicemail from the web

4/15/2025

Accessing voicemail from the web

To access your voicemail from a web browser:

1. Using your user credentials, log into GAX (*GAX IP address:port/gax*). If you are using Firefox, you might first need to install the QuickTime player.
2. Under **Operations > SIP Voicemail & Call Settings**, select a mailbox, which can belong to you personally or to a device or group to which you are assigned. If you have permission, you can:
 - Listen to or delete messages for any type of mailbox.
 - Control message playback: forward, rewind, pause, and adjust volume.
 - View the expiration date of each message (the date on which the system automatically deletes the message).
 - Click **Settings** and:
 - Change the mailbox password.
 - Activate a greeting that you have **recorded using the telephone**.
 - Enable or disable voicemail (only Group Mailbox Administrators can do so for group mailboxes).
 - View (but not set) the mailbox time zone and language.
 - **Group Mailbox Administrator only:** Click **Group Mailbox Notifications** to set email or web notification preferences. See **Voicemail notifications** for details.
 - To receive email notifications, select **On** from the **Email Notifications** menu, and type the group email address in the **Email** field. To stop receiving these notifications, select **Off** from the **Email Notifications** menu.
 - To receive web notifications, select **On** from the **HTTP Notifications** menu, and type the group phone number in the **Phone number** field. To stop receiving these notifications, select **Off** from the **HTTP Notifications** menu.

Dos and Don'ts:

- When accessing mailboxes through the web, you cannot use the mailbox number as your login. Use only your user credentials to log in to any associated device mailboxes.
- When you try to play a purged message, you hear "Sorry, this message has been deleted by another user."
- Until you delete them, expired messages count toward the maximum number of allowed messages.
- Automatic purging of voicemails does not reset the "new message" light on your phone.

Important

SIP Feature Server's UI has been deprecated from version **8.1.201.83** dated 09/14/16, and is not supported any further. Therefore, all administrative tasks must be performed using GAX.