



This PDF is generated from authoritative online content, and is provided for convenience only. This PDF cannot be used for legal purposes. For authoritative understanding of what is and is not supported, always use the online content. To copy code samples, always use the online content.

# Genesys Voice Platform

SSG Section

5/11/2025

## SSG Section

- CleanIntervalSecs
- ClientPortToTServer
- ConnRetryIntervalSecs
- fips\_enabled
- InitiatedCallRetryFlag
- MaxAttemptsLimit
- MaxDBConnPoolSize
- MinDBConnPoolSize
- pacing.BatchLimit
- pacing.caps.CallRequestsPerSecond
- pacing.EqualPriorityToNewAndOld
- pacing.NextRetryIntervalSecs
- pacing.PortLoadFactor
- pacing.QLowWatermark
- pacing.SlotCalculation
- PAssertedIdentityUsage
- RegRetryIntervalSecs
- ReqAccOnResourceDNErrTimeoutSecs
- ReqAccOnSIPSConnErrTimeoutSecs
- TimeToLiveLimitMins

### CleanIntervalSecs

**Default Value:** 180

**Valid Values:**

**Changes Take Effect:** After restart

Interval in seconds that determines how frequently SSG removes expired or completed requests from the DB.

### ClientPortToTServer

**Default Value:**

**Valid Values:**

**Changes Take Effect:** After restart

The local client side TCP port to be used for T-Lib transport. If this parameter is not specified, SSG will let the OS choose the local port.

### ConnRetryIntervalSecs

**Default Value:** 120

**Valid Values:**

**Changes Take Effect:** After restart

SSG attempts to re-connect to SIP Server in case of connection failure with SIP Server continuously in this interval.

## fips\_enabled

**Default Value:** False

**Valid Values:** True, False

**Changes Take Effect:** After restart

Specifies whether to enable FIPS mode in SSG. When FIPS mode is enabled, only FIPS 140-2 approved ciphers and algorithms can be used in SSL connections.

## InitiatedCallRetryFlag

**Default Value:** 1

**Valid Values:** 0, 1, 2, 3

**Changes Take Effect:** After restart

This parameter specifies how to process the requests present in the DB when SSG comes up. If the parameter value is set to 0 (zero), SSG deems all the initiated requests during SSG startup as failures and invokes notification URL for these requests. If it is set to 1, then SSG retries those requests. If the value is set to 2, then SSG deletes requests which are new and initiated. If the value is set to 3, then SSG deletes all the database requests

## MaxAttemptsLimit

**Default Value:** 25

**Valid Values:**

**Changes Take Effect:** After restart

The maximum attempts allowed (as system-wide upper limit) for outbound call requests from customer application.

## MaxDBConnPoolSize

**Default Value:** 7

**Valid Values:**

**Changes Take Effect:** After restart

The maximum number of database connections kept alive for use in SSG.

## MinDBConnPoolSize

**Default Value:** 3

**Valid Values:**

**Changes Take Effect:** After restart

The minimum number of database connections kept alive for use in SSG.

## pacing.BatchLimit

**Default Value:** TotalPorts

**Valid Values:**

**Changes Take Effect:** After restart

Total Number of requests, being fetched from DB in to the memory queue for processing in each cycle. If 'TotalPorts' is configured, SSG uses GVP total port capacity as obtained from SIP-S EventResourceInfo as the batch limit. if 'AvailPorts' is configured, SSG uses current available port capacity as obtained from SIP-S EventResourceInfo as the batch limit. Otherwise, user can configure any integer value as string, which will be used as the fetching limit.

## pacing.caps.CallRequestsPerSecond

**Default Value:** 30

**Valid Values:**

**Changes Take Effect:** After restart

This parameter controls the maximum calls per second that SSG shall initiate via SIP Server

## pacing.EqualPriorityToNewAndOld

**Default Value:** false

**Valid Values:** true, false

**Changes Take Effect:** After restart

In each fetch cycle from db, SSG gives equal priority to New and Old records if flag is set to true. Otherwise, New and Old records are not differentiated. If this option is set to true, increased DB fetches may result in some performance degradation.

## pacing.NextRetryIntervalSecs

**Default Value:** 10

**Valid Values:**

**Changes Take Effect:** After restart

This parameter dictates after how many seconds the call will be retried when temporary internal errors occur.

## pacing.PortLoadFactor

**Default Value:** 100

**Valid Values:**

**Changes Take Effect:** After restart

This parameter dictates how many outbound calls are initiated by SSG at a time. This is a % of the current GVP available port capacity.

## pacing.QLowWatermark

**Default Value:** 25

**Valid Values:**

**Changes Take Effect:** After restart

When In-Memory queue falls below this pre-defined % of total Batch Limit, SSG activates next fetching cycle.

## pacing.SlotCalculation

**Default Value:** Proportionate

**Valid Values:** Proportionate, Equal

**Changes Take Effect:** After restart

This parameter dictates how many records are allotted for an application in each database dip in every fetch cycle. If 'Proportionate' is configured, BatchLimit is divided among applications in the same ratio as their pending requests. If 'Equal' is configured, BatchLimit is divided equally among applications.

## PAssertedIdentityUsage

**Default Value:** 0

**Valid Values:**

**Changes Take Effect:** After restart

SSG includes this parameter under SIP\_HEADERS extension in TMakePredictiveCall. This parameter can be set to 0,1 or 2 values. Setting it to '0' makes SSG not to include the parameter as extension parameter. Setting it to '1' makes SSG map ANI AS-IS to this parameter and include in the SIP\_HEADERS extension. Setting it to '2' makes SSG extract the user part of the ANI and map it to this extension parameter.

## RegRetryIntervalSecs

**Default Value:** 120

**Valid Values:**

**Changes Take Effect:** After restart

SSG attempts to re-register the Resource DN in case of registraion failure with SIP Server continuously in this interval.

## ReqAccOnResourceDNErrTimeoutSecs

**Default Value:** 900

**Valid Values:**

**Changes Take Effect:** After restart

SSG rejects new requests from tenant applications if SSG fails to register Resource DN with SIP Server after the above time-out.

## ReqAccOnSIPSConnErrTimeoutSecs

**Default Value:** 900

**Valid Values:**

**Changes Take Effect:** After restart

SSG rejects new requests from tenant applications if SSG fails to connect to SIP Server after the above time-out.

## TimeToLiveLimitMins

**Default Value:** 1440

**Valid Values:**

**Changes Take Effect:** After restart

The maximum duration allowed (as system-wide upper limit) for outbound call requests from customer application.